

WM1824 Recommended Power Sequence

INTRODUCTION

The WM1824 2V_{RMS} DAC features ground referenced outputs and a DC servo to effectively eliminate power on pops and clicks.

The recommended power on/off sequence is very simple to implement, but there are a number of timing constraints that need to be followed to ensure the best possible performance.

These timing constraints will also be important in calculating if optimum power down pop performance can be achieved in emergency power down situations.

This document also stipulates the power-up to audio out timing, detailed in the recommended power on sequence section.

RECOMMENDED POWER ON SEQUENCE

- 1) To power up the device, apply AVDD and LINEVDD.
- 2) Wait for VMID to rise to $V_{\text{pord_hi}}$ and for AVDD/LINEVDD to rise above $V_{\text{pora_hi}}$ and settle. These timings will be dependent on the system design - see Table 2 for $V_{\text{pord_hi}}$ and $V_{\text{pora_hi}}$ typical voltage levels.
- 3) Start MCLK and BCLK and set $\overline{\text{MUTE}} = 1$. The device will be ready to output audio Δt after a logical AND of MCLK, BCLK, $\overline{\text{MUTE}}$ and $\overline{\text{POR}}$, as shown in Figure 1.

See Table 1 for Δt Power up to audio out timing – this is dependent on the sampling rate and MCLK frequency.




Figure 1 – Recommended Power-up sequence timing

SAMPLING RATE (LRCLK) (KHZ)	Δt POWER UP TO AUDIO OUT TIMING (ms)						
	128fs	192fs	256fs	384fs	512fs	768fs	1152fs
8	Unavailable	Unavailable	965	1003	849	502	481
11.025	Unavailable	Unavailable	700	728	616	365	350
16	Unavailable	Unavailable	483	502	425	252	241
22.05	Unavailable	Unavailable	351	365	309	183	176
32	Unavailable	Unavailable	242	252	213	127	121
44.1	Unavailable	Unavailable	176	183	155	92	Unavailable
48	Unavailable	Unavailable	162	168	143	85	Unavailable
88.2	239	263	89	92	Unavailable	Unavailable	Unavailable
96	220	241	82	85	Unavailable	Unavailable	Unavailable
176.4	120	132	Unavailable	Unavailable	Unavailable	Unavailable	Unavailable
192	111	121	Unavailable	Unavailable	Unavailable	Unavailable	Unavailable

Table 1 - Power up to audio out timing

Test ConditionsLINEVDD = AVDD = 3.3V AGND = LINEGND = 0V, $T_A = +25^\circ\text{C}$

PARAMETER	SYMBOL	TEST CONDITIONS	MIN	TYP	MAX	UNIT
Power Supply Input Timing Information						
VDD level to POR defined (LINEVDD/AVDD rising)	V_{pora}	Measured from LINEGND		158		mV
VDD level to POR rising edge (VMID rising)	V_{pord_hi}	Measured from LINEGND	0.63	0.8	1	V
VDD level to POR rising edge (LINEVDD/AVDD rising)	V_{pora_hi}	Measured from LINEGND	1.44	1.8	2.18	V
VDD level to POR falling edge (LINEVDD/AVDD falling)	V_{pora_lo}	Measured from LINEGND	0.96	1.46	1.97	V

Table 2 Power on Reset

Note: All values are simulated results

RECOMMENDED POWER OFF SEQUENCE

- 1) Set $\overline{\text{MUTE}} = 0$
- 2) Wait for shutdown time Δs (See Table 3)
- 3) Remove MCLK, AVDD and LINEVDD

Ensure that during the shutdown time (Δs) the BCLK and LRCLK are left running for 800 samples to allow the soft mute to assert fully. See Figure 2 for the timing diagram.

Note that in emergency shutdown situations (such as supply voltages collapsing) the shutdown must be completed before the $\overline{\text{POR}}$ is asserted to ensure best pop/click performance. This timing will be dependent on the system design - see Table 2 for V_{pora_lo} typical level.




Figure 2 - Recommended Power-down sequence timing

SAMPLING RATE (LRCLK) (KHZ)	Δs SHUTDOWN TIME (ms)						
	128FS	192FS	256FS	384FS	512FS	768FS	1152FS
8	Unavailable	Unavailable	693	731	577	422	422
11.025	Unavailable	Unavailable	504	532	420	307	307
16	Unavailable	Unavailable	349	368	291	213	213
22.05	Unavailable	Unavailable	254	268	212	156	156
32	Unavailable	Unavailable	177	186	148	109	109
44.1	Unavailable	Unavailable	129	136	108	80	Unavailable
48	Unavailable	Unavailable	91	96	77	59	Unavailable
88.2	183	183	67	70	Unavailable	Unavailable	Unavailable
96	168	168	67	70	Unavailable	Unavailable	Unavailable
176.4	94	94	Unavailable	Unavailable	Unavailable	Unavailable	Unavailable
192	86	86	Unavailable	Unavailable	Unavailable	Unavailable	Unavailable

Table 3 - Δs shutdown time

CONCLUSION

By following the timing constraints set out in this document, the customer can implement the optimum power up/down pop and click performance.

The customer can also calculate how long the device will take to power-up to audio out in their application, and how long the device will take to power down before it is safe to remove signals and power.

APPLICATION SUPPORT

If you require more information or require technical support, please contact the Wolfson Microelectronics Applications group through the following channels:

Email: apps@wolfsonmicro.com
Telephone Apps: +44 (0) 131 272 7070
Fax: +44 (0) 131 272 7001
Mail: Applications Engineering at the address on the last page

or contact your local Wolfson representative.

Additional information may be made available on our web site at:

<http://www.wolfsonmicro.com>

IMPORTANT NOTICE

Wolfson Microelectronics plc ("Wolfson") products and services are sold subject to Wolfson's terms and conditions of sale, delivery and payment supplied at the time of order acknowledgement.

Wolfson warrants performance of its products to the specifications in effect at the date of shipment. Wolfson reserves the right to make changes to its products and specifications or to discontinue any product or service without notice. Customers should therefore obtain the latest version of relevant information from Wolfson to verify that the information is current.

Testing and other quality control techniques are utilised to the extent Wolfson deems necessary to support its warranty. Specific testing of all parameters of each device is not necessarily performed unless required by law or regulation.

In order to minimise risks associated with customer applications, the customer must use adequate design and operating safeguards to minimise inherent or procedural hazards. Wolfson is not liable for applications assistance or customer product design. The customer is solely responsible for its selection and use of Wolfson products. Wolfson is not liable for such selection or use nor for use of any circuitry other than circuitry entirely embodied in a Wolfson product.

Wolfson's products are not intended for use in life support systems, appliances, nuclear systems or systems where malfunction can reasonably be expected to result in personal injury, death or severe property or environmental damage. Any use of products by the customer for such purposes is at the customer's own risk.

Wolfson does not grant any licence (express or implied) under any patent right, copyright, mask work right or other intellectual property right of Wolfson covering or relating to any combination, machine, or process in which its products or services might be or are used. Any provision or publication of any third party's products or services does not constitute Wolfson's approval, licence, warranty or endorsement thereof. Any third party trade marks contained in this document belong to the respective third party owner.

Reproduction of information from Wolfson datasheets is permissible only if reproduction is without alteration and is accompanied by all associated copyright, proprietary and other notices (including this notice) and conditions. Wolfson is not liable for any unauthorised alteration of such information or for any reliance placed thereon.

Any representations made, warranties given, and/or liabilities accepted by any person which differ from those contained in this datasheet or in Wolfson's standard terms and conditions of sale, delivery and payment are made, given and/or accepted at that person's own risk. Wolfson is not liable for any such representations, warranties or liabilities or for any reliance placed thereon by any person.

ADDRESS:

Wolfson Microelectronics plc
Westfield House
26 Westfield Road
Edinburgh
EH11 2QB
United Kingdom

Tel :: +44 (0)131 272 7000

Fax :: +44 (0)131 272 7001